



**ELECTRIC OIL PUMP 230V AUTO-START 10 L/MIN FREE  
FLOW 2,4 (24) MPA (BAR)**

MANUFACTURE AND DEVELOPMENT USING THE LATEST TECHNOLOGY

 [WWW.EUROLUBE.COM](http://WWW.EUROLUBE.COM)

## ELECTRIC OIL PUMP 230V AUTO-START 10 L/MIN FREE FLOW 2,4 (24) MPA (BAR)

Ideal solution when compressed air is not available. Self priming gear type pump, sintered precision gears and cast iron body with integrated adjustable by-pass valve in the pump body. Electronic control unit stops the pump automatically when control valve is closed and starts also automatically when control valve is opened again. Start pressure: 6 bar, stop pressure: 24 bar

### TECHNICAL DATA

Part No	60310
Capacity	10 l/min
Inlet	3/4" (F) BSPT
Outlet	1" (F) BSPT
Maximum working pressure	2,4 (24) MPa (bar)
Motor	780 W
Voltage	230 V AC
Pressure switch	Yes
IP	55
Packaging LxWxH	0,36 x 0,36 x 0,27 m
Weight (Gross)	16,8 kg
H.S. Code	84137045



## EUROLUBE EQUIPMENT

by Alentec & Orion AB, Grustagsvägen 4, SE-138 40 Älta, Sweden

EMAIL [eurolube@alentec.se](mailto:eurolube@alentec.se)

PHONE +46 (0)8-747 67 10

FAX +46 (0)8-715 20 74

 [www.eurolube.com](http://www.eurolube.com)